

11/09/00

IN THE UNITED STATES PATENT AND TRADEMARK OFFICE

UTILITY PATENT APPLICATION TRANSMITTAL

ASSISTANT COMMISSIONER OF PATENTS
Box Patent Application
Washington, D.C. 20231

Attorney Docket No. 20583.001
Prior Application Number: 08/835,339
Art Unit: 2739
Examiner: C. Lee
PTO Customer Number: unassigned

Sir:

Transmitted herewith for filing is a utility patent application of

Timothy Lee Erickson, 2208 Whyte Park Avenue, Walnut Creek, CA 94595

John Franklin Anthony Jurrius, 584 Turquoise Drive, Hercules, CA 94547

Lewis Clark McCoy, 3231 Vineyard, #5, Pleasanton, CA 94566

for: INTERCOM SYSTEM HAVING UNIFIED CONTROL AND AUDIO DATA TRANSPORT

ENCLOSED are the following:

1. ☒ Specification, abstract and claims of 23 Pages.
2. ☒ 7 sheets of ☒ formal ☐ informal drawings ☐ No drawings.
3. ☒ Declaration (original or copy) by the named inventor(s).
4. ☐ Preliminary Amendment
5. ☐ Information Disclosure Statement
6. ☐ Other:

NOTE the following:

7. ☐ Applicant is a small entity. Copy of Small Entity Statement enclosed – 50% Filing Fee Reduction (if applicable)
8. ☒ The prior application is assigned to Clear Com
9. This application is a:
☒ Continuation ☐ Divisional ☐ Continuation-in-Part (CIP) of Prior Application
Serial No. 08/835,339
Filed: April 7, 1997
10. ☐ Priority of the following application(s) is (are) claimed under 35 U.S.C. 119:

Serial No.	Date Filed	Country	Certified Copy of Priority Doc. Filed	
			USSN or PCT#	Date

11. ☐ An Extension of Time is filed concurrently herewith for the parent application.
12. ☐ Cancel claims _____ prior to calculation of the filing fee.

FILING FEE: calculated below (after accounting for any preliminary amendment or claims cancellations if noted above):

<input checked="" type="checkbox"/>	Total Claims	2	Total Claims Subject to Fees: 0	\$
<input checked="" type="checkbox"/>	Independent Claims	2	Total Claims Subject to Fees:	\$
<input type="checkbox"/>	Multiple Dependent Claims			\$
<input checked="" type="checkbox"/>	Basic Filing Fee			\$710.00
<input type="checkbox"/>	Extension Fees			\$
	Sub-Total			\$710.00
<input type="checkbox"/>	Less Small Entity Fee Reduction			\$
<input type="checkbox"/>	Assignment Recordal Fees			\$
	Total Fees			\$710.00

- ☒ Check(s) no. 473054 in the amount of \$710.00 is enclosed (must at least cover the basic fee). If no check or an insufficient check is enclosed and a fee is due herewith, the Commissioner is authorized to charge any fee or additional fee due in connection herewith to Deposit Account No. 03-3821, referencing Attorney Docket No. 20583.00111. **A duplicate of this sheet is enclosed.**
- ☒ The Commissioner is hereby authorized to charge any additional fees (or credit any overpayment) associated with this communication and which may be required under 37 CFR § 1.16 or 1.17 to Deposit Account No. 03-3821, referencing Attorney Docket No. 20583.00111. **A duplicate copy of this sheet is enclosed.**

Respectfully submitted,



By: Doyle B. Johnson
Registration No.: 39,240

Date: November 7, 2000

Crosby, Heafey, Roach & May
Two Embarcadero Center, Suite 2000
P.O. Box 7936, San Francisco, CA 94120-7936
(415) 543-8700, (415) 391-8269 Fax

Certificate of Mailing by "Express Mail"

Express Mail Mailing Label Number: EL588334340US

Date of Deposit: November 7, 2000

I hereby certify that this paper or fee is being deposited with the United States Postal Service By "Express Mail Post Office Addressee" Service under 37 CFR 1.19 on the date indicated Above and is addressed to the Assistant Commissioner for Patents, Washington, DC 20231

Nicole Broce
Name of Mailing Individual

Nicole Broce
Signature of Mailing Individual

INTERCOM SYSTEM HAVING UNIFIED CONTROL AND AUDIO DATA TRANSPORT

Timothy Lee Erickson
John Franklin Anthony Jurrius
Lewis Clark McCoy

CROSS-REFERENCE TO RELATED APPLICATIONS AND COPYRIGHT NOTIFICATION

This application depends for priority upon U.S. Provisional Patent Application Ser. No. 60/042,965 filed on April 4, 1997, entitled INTERCOM SYSTEM HAVING UNIFIED CONTROL AND AUDIO DATA TRANSPORT, and is a Continuation of U.S. Patent Application Serial No. 08/835,339 entitled INTERCOM SYSTEM HAVING UNIFIED CONTROL AND AUDIO DATA TRANSPORT. A portion of the disclosure of the parent Provisional Patent Application contains material which is subject to copyright protection. The copyright owners have no objection to the facsimile reproduction, by anyone, of the patent document or the patent disclosure as it appears in the patent and trademark office patent file or records, but otherwise reserve all copyright rights whatsoever.

FIELD OF THE INVENTION

The invention relates generally to multi-user intercom systems and, more specifically, to an intercom system providing a fail-safe, redundant and scaleable architecture implemented with digital Time Division Multiplexing technology for integrated audio and control data transport.

BACKGROUND OF THE INVENTION

Intercom systems provide communication between two or more remotely located individuals. More advanced intercom systems provide conference-type communication, simultaneously connecting several intercom stations so that several individuals can communicate with groups and sub-groups of other system users.

Conventional conference-type intercom systems include a switch matrix, commonly referred to as a crosspoint switch, which allows any user to communicate with any selectable mix of the remainder of the users. Crosspoint switches are normally used instead of direct point-to-point connections between source and destination equipment for all but the smallest implementations. A thorough discussion of prior art crosspoint switching schemes can be found in U.S. Patent No. 5,483,528 to Christensen, incorporated herein in its entirety by reference.

With crosspoint switches, all stations are connected directly to the crosspoint switch matrix which makes connections between the sources and destinations internally. In order to accommodate large numbers of switched audio channels, intercom systems typically distribute the crosspoint matrix across a number of bussed circuit modules or cards. Each module typically controls switch closures for connecting audio to or from a small group of intercom stations for which it is responsible. Each module typically employs a small local computer whose duties include, but are not limited to:

- (a) Making and breaking audio crosspoint closures;
- (b) Data communications with those intercom stations connected to it;
- (c) Data communications with other matrix modules via a central data communications controller.

1 A significant disadvantage of crosspoint switches is the geometrically increasing size and
2 cost of the switch matrix relative to the number of intercom users to be interconnected. For
3 example, although a four station matrix requires only 16 switches and an interconnect backplane
4 containing 4 circuit paths, a 100 station matrix requires 10,000 switches and dedication of 100
5 backplane circuit paths. Thus the available matrix-of-switches crosspoint topology is practical
6 only for relatively small systems.

7 Noise considerations also become more important as matrix-switch-based intercom
8 systems grow in size. Resistive summing of multiple analog sources into a common destination
9 results in signal-to-noise degradation. Driving multiple destinations from a single source
10 requires the addition of analog buffers to meet impedance-matching fanout requirements. These
11 buffers also degrade signal-to-noise performance.

12 Partially addressing these problems, the Christensen patent discloses a system which
13 interconnects intercom stations, making use of Time Division Multiplexing (TDM). In this
14 system, multiple audio signal sources (stations) are periodically sampled and digitized at a high
15 frequency and interleaved cyclically onto a parallel bus. At each destination (station) on the bus,
16 a receiver picks from the data stream the digitized samples associated with a given source or
17 combination of sources. It converts these signals to analog voltages and reconstructs the original
18 analog waveform or combination of waveforms by interpolating (integrating) between the
19 sequential samples taken from the bus.

20 Although TDM greatly improves the efficiency of audio transport in intercom systems,
21 traditional intercom systems (even the system disclosed in Christensen) suffer limitations in the
22 transport of the large volume of control data upon which intercom system operation depends.
23 Consider, for example, the requirement for any practical intercom system, that an audio
24 connection be established very quickly, and usually bi-directionally. Control messages must

1 pass between intercom stations over narrow bandwidth data channels, separate from the audio
2 channel, typically through an intermediary or central data communications controller to establish
3 the audio connection. The station initiating the conversation must notify the second station,
4 through the intermediary, that it desires to establish a talk-listen connection. The second station
5 then acknowledges the first station's request and replies with a request to establish its own
6 talk-listen connection, also through the intermediary processor. As system complexity and size
7 increase, the number of messages passed between stations escalates, and the limited bandwidth
8 of the data links, especially when implemented as serial data channels, tends to become a
9 bottleneck for data flow. If the intermediary processor and its communications links delay the
10 control message-passing to any great degree, the delay can become objectionable to users of the
11 intercom. The party attempting to initiate a conversation may begin to speak before the link is
12 established, causing the second party to receive a truncated, unintelligible message. The
13 common intercom topology employing serial control communications through an intermediary
14 processor, even including TDM-based audio signal transport, can be overwhelmed by the volume
15 of data transactions when an intercom system reaches a critical size.

16 Also, if the central communications processor malfunctions, the capacity for data
17 communication is lost and cannot be reestablished until the central processor is repaired or
18 replaced. Avoiding this failure mode by using redundant central communications processors
19 tends to be awkward and complicated.

20 An additional flaw in some available systems can be found in the use of the TDM bus for
21 transport of mixed and attenuated audio signals. This redundant use of the TDM bus narrows the
22 available bandwidth for more critical primary audio transport between stations and would
23 preferably be avoided.

1 Therefore, as demand grows for ever larger intercom systems, the industry needs a
2 mechanism which provides wider bandwidth data communications to support the increased
3 channel capacity of TDM audio transports. Preferably such a system would provide immunity
4 from catastrophic single-point failure without the appreciable complexity of redundant central
5 data communications processors.

SUMMARY OF THE INVENTION

To address the shortcomings of available crosspoint-based and TDM-based intercom systems which use a central communications and control processor as an intermediary in the transport of control signals between intercom stations, the present invention provides a network of peer processor-controlled circuit modules comprising a plurality of processor circuit modules connected to a common, time-division-multiplexed (TDM) bus, wherein bandwidth on the TDM bus is shared between a digital audio data transport and an inter-processor control message.

In a preferred embodiment, each of the processor circuit modules includes a control data communications circuit (CDCC) functioning as a communications co-processor and comprising means for automating the transmission and reception of simultaneous variable-length control messages among any number of the peer processor-controlled circuit modules using the TDM parallel bus, means for interleaving the control message with the audio data on the TDM parallel bus, and means for distributing the audio data and control data to a plurality of peripheral equipment stations capable of generating and receiving audio and control data. Means for providing automatic notification at every processor-controlled circuit module on the network when any other processor-controlled circuit module connects to or disconnects from the network is also provided for more rapid inter-processor communication

Although the modularity of this system may appear similar to available system designs with respect to the fact that interconnected circuit modules each manage traffic to and from groups of peripheral stations (such as intercoms), a fundamental distinction exists between this implementation and those available, in that no central intermediary or processor controls the overall system operation nor does any single processor or intermediary control data communications among modules. The invention provides vastly increased data communications bandwidth over the serial implementations previously employed by intercom systems, and

1 eliminates the risks of central processor failure in establishing and maintaining audio paths. This
2 new intercom system includes an audio signal attenuation and mixing scheme which does not
3 require mixed signals to re-enter the bus after attenuation and mixing is complete, thereby
4 allowing additional bandwidth for control and audio data transfer among intercom stations. A
5 primary advantage of the present invention is the high speed of control data transport among the
6 modules, as compared with existing serial data communications implementations employed in
7 existing intercoms.

8 Another advantage of the present invention is the economy of shared hardware resources
9 which manage both audio transport and data communications.

10 Another advantage of the present invention is the safety from catastrophic single-point
11 failure previously associated with a hierarchical communications scheme, i.e. a single central
12 communications and control processor over multiple slave controllers.

13 Still another advantage of the present invention is the small size of the system hardware.

14 Still another advantage of the present invention is the bus-independent attenuation and
15 mixing scheme provided.

16 Still another advantage of the present invention is the re-configurability of the intercom
17 system layout and features.

18 Yet another advantage of the present invention is the scaleable nature of the provided
19 architecture, providing the ability to interconnect over a thousand stations on a single distributed
20 system.

1 Another advantage of the present invention is the ability to integrate available digital
2 phone line technology to provide a geographically distributed, reliable intercom system to a large
3 group of users.

BRIEF DESCRIPTION OF THE DRAWINGS

The aforementioned advantages of the present invention as well as additional advantages thereof will be more clearly understood hereinafter as a result of a detailed description of a preferred embodiment of the invention when taken in conjunction with the following drawings in which:

FIG. 1 is a simplified block diagram of the intercom system of the present invention;

FIG. 2 is a block diagram of a Matrix Card used in the intercom system of the present invention;

FIG. 3 is a block diagram of a Configuration Card used in the intercom system of the present invention;

FIG. 4 is a diagram of that portion of dual-port RAM used to provide data queues in conjunction with the CDCC described below, in the intercom system of the present invention, wherein lines 132, 134, and 136 provide interconnect to the CDCC block illustrated in FIG. 5;

FIG. 5 is a block diagram of the preferred Control Data Communications Circuit (CDCC) employed on the Configuration Card of FIG. 2 and the Matrix Card of FIG. 2, wherein lines 132-138 provide interconnect to the dual-port RAM portion illustrated in FIG. 4 and other resources on the Matrix Card illustrated in FIG. 2;

FIG. 6 illustrates the manner in which Audio Data transport and Control Data Communication share the TDM Time Frame in the system of the present invention;

1 FIG. 7 is a block diagram illustrating a preferred hardware audio circuit implemented in
2 an application specific integrated circuit on the Matrix Card of FIG. 2;

3 FIG. 8 illustrates a scaled architecture including a plurality of systems illustrated in
4 FIG. 1 interconnected to create a system having far greater user capacity while maintaining
5 optimal audio bandwidth.

DETAILED DESCRIPTION OF THE DRAWINGS

FIG. 1 provides a system-level block diagram of the intercom of the present invention. TDM Data Bus 160 and TDM Control Bus 158 interconnect the cards in the intercom system matrix rack. Sixteen-bit-wide TDM Data Bus 160 provides transport for audio among all Matrix Cards 2 and provides inter-processor communication among all Matrix Cards 2 and the Configuration Card 4. The only system card not attached to the TDM Data Bus 160 is the primary clock card 8 which possesses neither intelligence nor communications capability.

TDM Control Bus 158 provides system-wide synchronized timing signals to all cards 2 and 4, thereby providing the foundation for data flow across TDM bus 160. TDM Control Bus 158 consists of Primary and Secondary (Backup) Clock Groups, generated respectively on the Primary Clock Card 8 and the Configuration Card 4. Circuitry on the Configuration Card 4 continuously monitors the quality of signals in the Primary and Secondary Clock Groups and arbitrates system use of these signals.

The presently preferred embodiment of the intercom system includes as many as twenty-five Matrix Cards 2 and two hundred intercom stations 6, although a plurality of systems may be linked, resulting in a much larger overall count of interconnected stations, in a manner discussed below. The system illustrated in FIG. 1 includes "N" Matrix Cards 2, numbered for reference from # 1 to #N. Eight intercom stations 6 may be connected to each Matrix Card 2 in the presently preferred embodiment, but more may be accommodated in a manner depending upon packaging constraints. It should be noted that stations 6 are denoted as intercoms because these are anticipated as the most common audio and data peripheral equipment to be used within the inventive system. However, any audio and/or data generating and/or receiving peripheral may be used, e.g., telephones, control equipment, and satellite link-up equipment.

1 The Primary Clock Card 8 is the source of Primary TDM Clock and Synchronization
2 signals which are broadcast to all other cards in the system over the TDM Control Bus 158.
3 Configuration computer 70 is connected to Configuration Card 4 via an RS-232, Ethernet, or
4 compatible local connecting mechanism, providing a friendly interface to an intercom system
5 user for modifying system configuration and events.

6 FIG. 2 provides a block diagram illustrating relevant features of Matrix Card 2. Control
7 Application Specific Integrated Circuit (ASIC) 10 and Audio ASICs 140 are preferably very
8 large gate arrays or field programmable gate arrays (FPGAs), but possibly any other device(s) of
9 sufficient density and possessing a definable internal architecture. Taken together as a
10 subsystem, these ASICs provide the core functions required of a Matrix Card 2, providing the
11 audio and control data interface between eight intercom stations 6 and the TDM bus 160. As
12 similar control ASIC 610 resides on the Configuration Card 4, as shown in FIG. 3.

13 Referring to FIGS. 2 and 3, on both cards 2 and 4 non-volatile ROM blocks 202 provide
14 the code memory for a local microprocessor 30 and preferably comprises a flash-type memory to
15 allow remote code revision without memory device replacement. At system power-up, or
16 whenever a new Matrix Card 2 is hot-patched into a system under power, Matrix Card
17 configuration information is loaded into a configuration data volatile memory 204 (RAM) on
18 Matrix Card 2 Configuration Card 4. The loaded data describes for example, the function and
19 electronic labeling of distinct switches at intercom stations 6 connected to the newly connected
20 or newly powered-up Matrix Card 2, and the groupings of intercom stations 6 throughout the
21 system for ease of use by a plurality of users each having different communications needs for the
22 system. Control ASIC 10 implements the main interface and processing circuitry for audio and
23 control data flow between the Matrix Card 2 and the remainder of the system, including audio
24 ASIC interface block 211, CODEC timing block 212, frame and station service request block
25 213, I/O decode block 214, Control Data Communications Circuit (CDCC) block 100, data

1 routing block 216, and dual-port RAM address control timing block 217. A detailed block
2 illustration of preferred Control Data Communications Circuit (CDCC) 100, used on Matrix
3 Card 2 and Configuration Card 4, and implemented in control ASICs 10 and 610 (along with
4 additional circuitry not shown) is shown in FIG. 5. Other circuitry, some of which is common to
5 all types of embedded control applications, needs no further amplification here.

6 Configuration Card 4 provides several important system functions, but is preferably
7 neither a repository of central control nor an arbiter of communications over other system cards.
8 Its primary functions are to:

- 9 (a) provide (preferably multiple sets of) globally accessible configuration data for all
10 system parameters;
- 11 (b) provide Secondary Clock Group signal generation
- 12 (c) monitor Primary and Secondary Clock Group signal quality
- 13 (d) dictate system-wide choice of Primary or Secondary Clock Group signals;
- 14 (e) communicate with Configuration PC 70 to acquire new system configuration data
15 and log system events;
- 16 (f) provide miscellaneous system monitoring functions, such as temperature
17 measurement and alarm monitoring;
- 18 (g) provide real-time clock maintenance by utilizing clock arbitration block 218 and
19 clock generation block 219 in combination with reference clock 220.

20 The reader should note that Configuration Card 4 need not be present in an operating
21 intercom system to send audio or control messages from one Matrix Card 2 to another. The
22 intercom system will continue to operate without any interruption in audio transport or

1 interruption in the capacity to make and break connections between stations even if the
2 Configuration Card 4 is unplugged during system operation.

3 As the Control Data Communication Circuit (CDCC) 100 in Control ASICs 10 and 610 is
4 common to the core logic on the Matrix Card 2 and the Configuration Card 4, we will begin with
5 a discussion of this important topic.

6 Referring to FIG. 5, fundamental to the present invention's inter-card data
7 communications is the Control Data Communications Circuit (CDCC) 100. CDCC 100 resides
8 in the control ASICs 10 and 610 on all Matrix 2 and Configuration 4 Cards, respectively. Both
9 Matrix Card 2 and Configuration Card 4 will be collectively referred to as "cards" for the
10 remainder of this discussion, since for the purposes of this discussion the CDCCs on both card
11 types possess, by design, much of the same hardware, are driven by similar communications
12 software, and exhibit substantially identical behavior. CDCC 100 automates multiple
13 variable-length block data transfers simultaneously among any number of these cards on the
14 TDM Data Bus 160, thereby relieving the system of the requirement for a centralized,
15 intermediary processor. CDCC 100 comprises transmitter and receiver sections which interface
16 to a single source (transmit) queue 205 in dual-port RAM 20 local to the same card and a
17 plurality of destination (receive) queues 210, also in dual-port RAM 20.

18 As a control-message source, the transmit portion of each CDCC 100 in the intercom
19 system may specify either a unique destination card receiver (which may even be the receiver on
20 the transmitting card itself) or a global (multi-card) destination for a given message. The
21 receiver portion of each CDCC 100 automatically acquires all control-messages for which it is
22 the intended recipient, even when a plurality of cards simultaneously send it messages. This
23 network implementation results in the transport of multiple simultaneous control messages
24 without contention for hardware resources unlike existing serial communications

1 implementations. The intercom incurs no software arbitration overhead since the protocol is
2 almost entirely implemented in hardware; the CDCC receiver portion is not overloaded even if it
3 simultaneously receives control-messages from every card in the intercom system since it has a
4 separate receive queue 210 for each possible message source.

5 A CDCC 100 manages the movement of blocks of data among multiple cards 2 and 4
6 using a portion of the bandwidth (refer to FIG. 6) of the TDM Data Bus 160. Each CDCC
7 contains transmitter and receiver components whose common timing elements are synchronized
8 by TDM frame synchronizing signals. (For the sake of brevity, source and destination
9 components of CDCCs will be referred to as labeled in FIG. 5; the reader should understand that
10 source and destination components are included on all CDCCs.)

11 In moving variable-length data blocks, each card's local microprocessor 30 and the
12 CDCC 100 both access data queues from opposite sides of shared dual-port RAM 20. In sending
13 a message, the microprocessor 30 stores data to a transmit (XMIT) queue 205. The CDCC
14 transmitter automatically reads queue 205 and dispatches appropriately-timed data onto TDM
15 bus 160 from it. Upon completion, the CDCC 100 transmitter portion interrupts the source card
16 microprocessor 30 to indicate the availability of transmit queue 205 for the next message.
17 CDCC receiver circuitry at the destination card automatically recognizes all data for which it is
18 the intended recipient and places each incoming TDM datum into the receive queue 210 in
19 dual-port RAM 20 associated with the address of the transmitting CDCC. After receiving a
20 complete message, the destination CDCC interrupts its local microprocessor 30, which reads an
21 internal register in the CDCC indicating which receive queue(s) contain(s) the new message(s).

22 Describing the process of sending a control message to a destination card in greater
23 detail, the microprocessor 30 at the source card 2 or 4 performs three steps : First, the
24 microprocessor 30 loads a variable-length message into the region in the dual-port RAM 20

reserved to hold the CDCC's transmit queue 205, and retains the location of the last message word (offset address from start-of-queue) through the second step, below; Second, the source microprocessor 30 writes the destination card's identity (address) in its Destination Address Register 110; Third, the source microprocessor 30 establishes the size of the variable-length message to be sent by specifying to its CDCC transmitter the location of the highest numbered data word in its transmit queue 205. This third step is accomplished by loading the offset of the last message word (retained from the first step, above) into its CDCC's Word-In-Queue Register 112. The CDCC's transmit hardware portion offsets the base address of its transmit queue 205 with the Word-In-Queue Register 112 and uses that combined address to fetch the (highest-numbered) first word of the message from its own transmit queue 205 in dual-port RAM 20. As the message is sent, the Word-In-Queue is regenerated at the receiver (described below) and the receiver uses this address offset to place the message data into the same-numbered location(s) in its receive queue 210. In loading its Word-In-Queue Register 112, the source microprocessor 30 triggers the process whereby the CDCC 100 transmit hardware portion automatically dispatches the message, one word per TDM frame, onto TDM bus 160 without further microprocessor 30 intervention. CDCC 100 transmitter hardware portion then concatenates the address byte from the destination CDCC's Address Register 110 with the Word-In-Queue Register 112 to form a Composite Destination Address Word 163, which is broadcast on TDM data bus 160 during the first time-slot of the time-slot pair assigned to the source card (based on the card's system address). Reference to FIG. 6, below, provides slot-pair structure details.

During each TDM frame, each CDCC 100 drives the TDM bus 160 during a particular, pre-designated time-slot pair determined by the source microprocessor's unique system address stored at register 133. As illustrated in FIG. 6, the first time-slot within the slot pair contains the source CDCC's Composite Destination Address Word 163, which includes both the Destination Card Address in the high byte 162 of the Composite Destination Address Word 163 and the

1 Word-In-Queue address at low byte 164 of the Composite Destination Address Word 163.
2 During the second time-slot of the pair, designated the Control Data Word Time-Slot 166, the
3 source CDCC places a control data word from it's transmit queue 205 onto TDM bus 160.
4 Down-counter 114 automatically decrements Word-In-Queue Register 112 as each successive
5 word of control data is transmitted. After sending the last word of the control message, in
6 successive data frames, the source CDCC recognizes that Word-In-Queue Register 112 has
7 decremented through zero and generates an interrupt (IRQ) to notify its microprocessor 30 that
8 its transmit queue 205 is empty and available for the next message.

9 After transmit queue 205 is emptied, and until local microprocessor 30 gives the CDCC
10 100 transmitter hardware portion new data to transmit along with a new destination address, the
11 CDCC transmitter hardware portion remains in an Idle state. While Idle, the CDCC transmitter
12 hardware portion continues to drive TDM bus 160 within its assigned time-slot pair with a
13 Composite Destination Address Word 163 that points to a non-existent destination card, but
14 identifies this CDCC's card 2 or 4 as active in the intercom system. In fact, each card active on
15 the intercom system's peer network transmits a Composite Destination Address Word 163 during
16 the first time-slot of the time-slot pair assigned to that card on the basis of its unique system
17 address, without regard to whether it is in an Idle state. The contents of this word is always
18 distinguishable from the state of the undriven bus; every card's CDCC-100 receiver hardware
19 portion inspects the contents of TDM bus 160 during all such time-slots and thereby determines
20 which other cards 2 or 4 are connected to the network without polling the network for resident
21 cards. The inventive CDCC 100 takes advantage of this fact by mapping the connection state of
22 each card in the system to a bit in the multiple-word Card Population Register 120. Each card's
23 CDCC provides additional circuitry which detects changes in the connection status of cards and
24 generates a microprocessor 30 interrupt (IRQ) when any card joins or leaves the intercom
25 system.

1 When the hardware receiver portion at the destination CDCC 100 recognizes its own
2 address in the Destination CDCC Address field of a Composite Destination Address Word 163 at
3 comparator 140, or recognizes a global message address at comparator 141, it accepts the word
4 placed in the next time-slot on the TDM bus as message data intended for itself. The CDCC's
5 Receiver Address Generator 142 determines which receive queue 210 will receive the new data,
6 having derived the address of the source from observation of the time-slot during which the
7 matching Composite Destination Address Word 163 was received. Data received from card 1 is
8 routed to queue 1, etc. The receiver CDCC places the data in a location in that queue specified
9 by the Destination Word-In-Queue field of the Composite Destination Address Word 163. For
10 example, data received from the source card's transmit queue 205 word number 17 is routed to
11 the appropriate receive queue 210 word number 17, etc. When the destination CDCC recognizes
12 that the incoming Word-In-Queue field has finally decremented to zero, indicating the reception
13 of the last data word, it interrupts its local microprocessor 30, and indicates by means of the
14 Frame and Station Service Request block 213 which receive queue 210 contains the new
15 message.

16 Turning next to the manipulation of audio signals and referring to FIG. 2, the Matrix
17 Card 2 core logic subsystem acquires, from the encoder sections of serial CODECs 50, bit
18 streams representing audio signals from each of the intercom stations connected to its Matrix
19 Card 2. It should be noted that the preferred system includes a single, dual-use CODEC 50 for
20 every two intercom stations 6. The core logic synchronously converts this audio signal data to a
21 form which it places on TDM bus 160 during a specific group of audio time-slots, based on the
22 card's physical location (address) in the intercom rack, as illustrated in FIG. 6. Each card in turn
23 places its group of digitized audio samples onto the TDM bus. From these data, all cards can
24 sample any of two hundred channels of interest in a fully populated system.

1 The Matrix Card 2 core logic subsystem connects audio sources on TDM bus 160 to each
2 of eight local station destinations 6, as if connected through a crosspoint switch. However, in
3 this implementation the "switch" possesses faders (not shown) at the input to every crosspoint, a
4 concept termed Variable Listen Levels. In other words, the core logic of Matrix Card 2 enables
5 each destination station 6 to receive audio from any conceivable mix of the stations which
6 communicate through the Matrix Cards 2 in the intercom system to TDM bus 160, as if
7 connected by a crosspoint switch. However, by means of Variable Listen Levels in the current
8 invention, each station's audio contribution can be individually adjusted relative to that of the
9 other stations in the mix. This feature is useful in establishing a hierarchy of users, where some
10 important user, perhaps a director or producer, needs to be monitored at a higher level than other
11 audio sources, yet not completely kill the other sources in the mix. An intercom user may also
12 employ Variable Listen Levels to boost the level of a soft speaker (or attenuate a loud one)
13 relative to other users of the intercom, by means of depressing a key (not shown) on intercom
14 station 6. Variable Listen Levels enables the current invention to provide a unique related
15 feature, called Psycho-acoustic Level Control. This term applies to the situation in which the
16 user of an intercom who wishes to boost the level of a particular station eventually runs out of
17 gain because of an exceptionally weak audio signal on the channel of interest. In the current
18 invention, when no additional boost is available to listen to a particular channel, successive
19 key-presses intended to raise the volume of a desired signal instead automatically attenuate the
20 other signals in the mix. This gives the user the impression of increasing the loudness for the
21 channel of interest. To accomplish this mixing of audio with Variable Listen Levels, the core
22 logic of Matrix Card 2 possesses eight identical audio acquisition circuits providing audio to a
23 destination station connected to a Matrix Card 2 (refer to FIGS. 2, 6, and 7). Circuitry in the
24 Control ASIC 10 portion of the core logic simultaneously fetches an audio sample from the
25 TDM bus and attenuation data from dual-port RAM 20, during each of the two hundred audio
26 data slot-times in the TDM frame illustrated in FIG. 6. The attenuation data across lines 704 and
27 audio sample across lines 706 meet at an attenuator circuit 702 shown in FIG. 7, where the

1 attenuation data effectively provides the connection for a particular channel of audio data to the
2 destination station, as follows: If the attenuation data indicates infinite attenuation, the TDM
3 data from that source station is not connected to the destination station; if the attenuation data
4 indicates no attenuation, then the station currently being sampled is mixed in at full volume;
5 other attenuation values provide for variable amounts of the source signal to be passed into the
6 mix of signals. After attenuation, whatever remains of a station's audio sample next passes to an
7 accumulator 708 which arithmetically sums two-hundred sequential values at its input. Most of
8 these values are zero under normal circumstances, since the user rarely desires to simultaneously
9 listen to two-hundred stations. Attenuator 702 provides several bits of headroom to allow for the
10 occurrence of out-of-range sums without numeric wrap-around. Clipper 710 cleanly removes
11 these bits. The bulk of the remainder of the logic relating to the audio deals with synchronizing
12 the serial interlaced bit streams from the audio CODECs 50 with the ongoing TDM activity.

13 Referring next to FIG. 8, a large-scale system architecture is provided, comprising a
14 plurality of the systems 1 shown in FIG. 1 interconnected either locally or across long distance
15 spans using digital telephone line connections, such as T-1 telephone lines. The plurality of
16 systems are preferably interconnected by substituting a system interconnect card 11 for one
17 Matrix Card 2 in a central system. Instead of connecting to up to eight intercom stations 6 (as
18 would a Matrix Card 2), interconnect card 11 connects to up to eight additional intercom systems
19 1, each potentially having its own interconnect card 11 which may connect to still additional
20 systems 1. While interconnect cards 11 are very similar to Matrix Cards 2 described above, there
21 are minor distinctions intended to deal with system addressing which will be understood by those
22 skilled in the art to which the present invention pertains.

23 While the present invention has been described with reference to certain preferred
24 embodiments, those skilled in the art will recognize that various modifications and other
25 embodiments may be provided. These other embodiments are intended to fall within the scope

1 of the present invention. For example, larger system bus widths may be utilized to increase
2 system throughput and are clearly within the scope and spirit of this description. Similarly,
3 alterations may be made to the layout of CDCC 100 without sacrificing the ability to transport
4 control data from peer to peer in the intercom system without utilizing a single intermediary
5 processor. In addition, the control data transport mechanism of the described intercom system
6 may be incorporated into other electronic systems wherein high speed control communication is
7 desired or necessary. Accordingly, all such modifications and additions are deemed to be within
8 the scope of the invention which is to be limited only by the claims appended hereto.

9 CLAIMS

10 What is claimed is:

11 1. An intercom system for transferring audio information and data information
12 among a plurality of users, the intercom system comprising:
13 a common, time-division-multiplexed parallel bus;
14 a plurality of circuit modules connected to the bus, each one of the circuit modules being
15 connected to at least one peripheral station for control message and audio data interface between
16 the peripheral stations and the bus;
17 each circuit module having a control data communication circuit having a receiver and a
18 transmitter, the transmitter having assigned transmit time slots for transferring control messages
19 onto the bus, the transmitter being configured for transmitting, in successive time slots, data
20 identifying a unique address, each receiver being configured for distinguishing the address data
21 received on the bus during a designated receive time slot for automatically determining which of
22 the circuit modules is a source of a control message datum.

23 2. An intercom system for transferring audio information and data information
24 among a plurality of users, the intercom system comprising:

1 a common, time-division-multiplexed parallel bus;
2 a plurality of matrix cards connected to the bus, each matrix card having at least one
3 intercom station connected to it for audio and control data interface between the stations and the
4 bus;
5 each matrix card having a control data communication circuit having a receiver and a
6 transmitter, the transmitter having assigned transmit time slots for transferring data onto the bus,
7 the transmitter being configured for transmitting; in successive time slots, data identifying a
8 unique address, each receiver being configured for distinguishing the address data received on
9 the bus during a designated receive time slot for automatically determining which matrix cards
10 are connected to the bus.

11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2

INTERCOM SYSTEM HAVING UNIFIED CONTROL AND AUDIO DATA TRANSPORT

Timothy Lee Erickson
John Franklin Anthony Jurrius
Lewis Clark McCoy

ABSTRACT

An intercom system utilizing peer-to-peer computer network hardware that shares bandwidth between digital audio transport and inter-processor data communications on a common time-division-multiplexed (TDM) parallel bus. The system hardware automates symmetric, simultaneous, variable-length data block transfers among all of the microprocessor-controlled cards in the system. These cards communicate without intervention by or assistance from a central controller or intermediary communications processor, thereby improving system throughput and reliability and decreasing system complexity. An additional benefit of the communication scheme employed herein is that all system cards automatically track changes in the population of other cards in the system. The intercom system described employs a Configuration Card connected to a configuration computer to provides the system supervisor with the ability to quickly configure the system for a particular use without altering the system's hardware configuration.




FIG. 1




FIG. 8




FIG. 2




FIG. 3





FIG. 4

FIG. 5






FIG. 5B

AUDIO DATA AND CONTROL DATA SHARING COMMON TDM RESOURCES




FIG. 6

**COMBINED DECLARATION FOR PATENT APPLICATION
AND POWER OF ATTORNEY**

As a below named inventor, I hereby declare that:

My residence, post office address and citizenship are as stated below next to my name,

I believe I am the original, first and sole inventor (if only one name is listed below) or an original, first and joint inventor (if plural names are listed below) of the subject matter which is claimed and for which a patent is sought on the invention entitled

INTERCOM SYSTEM HAVING UNIFIED CONTROL AND AUDIO DATA TRANSPORT

the specification of which (check one) ☐ is attached hereto or ☒ was filed on April 7, 1997 as Application Serial No. 08/835,339 and was amended on (if applicable).

I hereby state that I have reviewed and understand the contents of the above-identified specification, including the claims, as amended by any amendment referred to above.

I acknowledge the duty to disclose information which is material to the examination of this application in accordance with Title 37, Code of Federal Regulations, Section 1.56(a).

I hereby claim foreign priority benefits under Title 35, United States Code, § 119 of any foreign application(s) for patent or inventor's certificate listed below and have also identified below any foreign application for patent or inventor's certificate having a filing date before that of the application on which priority is claimed:

Prior Foreign Application(s)			Priority Claimed	
			Yes	No
Number	Country	Day/Month/Year Filed		

I hereby claim the benefit under Title 35, United States Code, § 120 of any United States application(s) listed below and, insofar as the subject matter of each of the claims of this application is not disclosed in the prior United States application in the manner provided by the first paragraph of Title 35, United States Code, § 112, I acknowledge the duty to disclose material information as defined in Title 37, Code of Federal Regulations, § 1.56(a) which occurred between the filing date of the prior application and the national or PCT international filing date of this application:

60/042,965

April 4, 1997

Pending

Application Ser. No.

Filing Date

Status: Patented, Pending, Abandoned

I HEREBY APPOINT THE FOLLOWING AS MY ATTORNEYS WITH FULL POWER OF SUBSTITUTION TO PROSECUTE THIS APPLICATION AND TRANSACT ALL BUSINESS IN THE PATENT OFFICE CONNECTED THEREWITH: Malcolm B. Wittenberg, Registration No. 27,028, Nathan P. Koenig, Registration No. 38,210, Adam H. Tachner, Registration No. 40,343, and Vincent E. Duffy, Registration No. 39,964.


Send correspondence to:

Adam H. Tachner, Esq.
Crosby, Heafey, Roach & May
1999 Harrison Street
P.O. Box 2084
Oakland, California 94604-2084
Telephone: (510) 763-2000
Facsimile: (510) 273-8832

I hereby declare that all statements made herein of my own knowledge are true and that all statements made on information and belief are believed to be true; and further that these statements were made with the knowledge that willful false statements and the like so made are punishable by fine or imprisonment or both, under Section 1001 of Title 18 of the United States Code and that such willful false statements may jeopardize the validity of the application or any patent issued thereon.

Full name of sole or first inventor Timothy Lee Erickson

Inventor's signature



11/17/97

Date


Residence 2208 Whyte Park Avenue, Walnut Creek, CA 94595

Citizenship U.S.A.

Post Office Address 2208 Whyte Park Avenue, Walnut Creek, CA 94595

Full name of second joint inventor, if any, John Franklin Anthony Jurrius

Inventor's signature



11/17/97

Date

Residence 584 Turquoise Drive, Hercules, CA 94547

Citizenship

~~U.S.A.~~


Canadian



Post Office Address 584 Turquoise Drive, Hercules, CA 94547

Full name of third joint inventor, if any, Lewis Clark McCoy

Inventor's signature



11/17/97

Date

Residence 3231 Vineyard, #5, Pleasanton, CA 94566

Citizenship U.S.A.

Post Office Address 3231 Vineyard, #5, Pleasanton, CA 94566

4095981

4095981